



**ELECTRONICS, INC.**  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089

## NTE1714M Integrated Circuit Remote Control Amplifier/Detector

**Description:**

The NTE1714M is an integrated circuit in an 8-Lead DIP type package designed for use in infrared remote control applications. It provides the high gain and pulse shaping needed to couple the signal from an IR receiver diode to the tuning control system logic.

**Features:**

- High Gain Pre-Amp
- Envelope Detector for PCM Demodulation
- Simple Interface to Microcomputer Remote Control Decoder
- May be Used with Tuned Circuit for Narrow Bandwidth, Lower Noise Operation
- Small Package Size
- Minimum External Components
- Wide Operating Supply Voltage Range
- Low Current Drain

**Absolute Maximum Ratings:**

Supply Voltage,  $V_{CC}$  ..... 15V  
 Power Dissipation, Package Rating  $P_D$  ..... 1.25Watts  
     Derate above 25°C. .... 10mW/°C  
 Operating Temperature Range,  $T_A$  ..... 0° to +75°C  
 Storage Temperature Range,  $T_{stg}$  ..... -55° to +125°C  
 Junction Temperature,  $T_J$  ..... +150°C

**Recommended Operating Conditions:**

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Power Supply Voltage	$V_{CC}$	$T_A = +25^\circ\text{C}$	4.75	-	15.0	V
		$T_A = 0^\circ\text{C}$	5.0	-	15.0	V
Input Frequency	$f_{in}$		30	40	80	kHz

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$ ,  $V_{CC} = 5\text{V}$ ,  $f_{in} = 40\text{kHz}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Power Supply Current	$I_{CC}$		1.5	2.5	3.5	mA
Input Terminal Voltage	V (Pin7)		2.4	2.8	3.0	V
Input Voltage Threshold	$V_{in}$		–	50	100	$\mu\text{V}_{P-P}$
Input Amplifier Voltage Gain	$A_V$	V (Pin3) = $500\text{mV}_{P-P}$	–	60	–	dB
Input Impedance	$r_{in}$		40	60	80	$\text{k}\Omega$
Output Voltage	$V_{OL}$	$V_{in} = 1\text{mV}_{P-P}$	–	–	0.5	V
	$V_{OH}$	Input Open	–	–	5.0	V
Output Leakage Current	$I_{OH}$	$V_{CC} = V_{OH} = 15\text{V}$	–	–	2.0	$\mu\text{A}$

**Pin Connection Diagram**

