

# **11-MD142**

---

**Version : A.003  
Issue Date : 2005/11/7  
File Name : SP-MD142-A.003.doc  
Total Page : 11**

## ***Multi-Channels Motor Driver For DSC***



**新竹市展業一路 9 號 7 樓之 1**

**SILICON TOUCH TECHNOLOGY INC.**

**9-7F-1, Prosperity Rd I, Science-Based Industrial Park**

**Hsinchu, Taiwan, R.O.C.**

**Tel : 886-3-5645656      Fax : 886-3-5645626**

---

11-MD142

# *Motor Driver For DSC*

## **General Specifications**


The 11-MD142 is a 4-channels motor driver for Digital Still Camera. It contains constant current control for M-shutter and saturation voltage control channels for AF stepping motor and Iris. It is optimal for DSC Lens module in M-shutter, Iris and Auto Focus motor.

## Features and Benefits


- Low voltage operation
  - Low saturation voltage
  - Low input current
  - Easy constant current control
  - Ultra low standby current
  - Reference Voltage inside ( $V_{ref}=1.23V$ )
  - Thermal shutdown protection
  - Thin, highly reliable package :QFN-32(4.75mm X 4.75mm) and TSSOP-20

## Pin Assignment

## ***Pin Assignment of QFN-32***



## *Pin Assignment of TSSOP-20*





## Pin Descriptions of QFN-32

Pin NO.	Pin Name	Description	Pin NO.	Pin Name	Description
1	PIM	Current sense resistor	17	NC	
2	EN1	Mode Selected Input pin	18	OUT6	Motor output pin
3	EN2	Mode Selected Input pin	19	OUT5	Motor output pin
4	IAD	AMP positive input pin	20	OUT4	Motor output pin
5	IN1	Motor control input pin	21	OUT3	Motor output pin
6	IN2	Motor control input pin	22	OUT2	Motor output pin
7	IN3	Motor control input pin	23	GND	Controller and driver ground
8	IN4	Motor control input pin	24	NC	
9	NC		25	IM	Current sense resistor
10	NC		26	GND	Controller and driver ground
11	NC		27		
12	VB	Power supply pin for motor driver	28	OUT1	Motor output pin
13	VREF	Reference voltage output pin	29	NC	
14	GND	Motor driver ground	30	NC	
15	NC		31	NC	
16	NC		32	VDD	Power supply pin for controller.

## Pin Descriptions of TSSOP-20

Pin NO.	Pin Name	Description	Pin NO.	Pin Name	Description
1	VDD	Power supply pin for controller.	11	VREF	Reference voltage output pin
2	PIM	Current sense resistor	12	GND	Motor driver ground
3	EN1	Mode selected Input pin	13	OUT6	Motor output pin
4	EN2	Mode selected Input pin	14	OUT5	Motor output pin
5	IAD	AMP positive input pin	15	OUT4	Motor output pin
6	IN1	Motor control input pin	16	OUT3	Motor output pin
7	IN2	Motor control input pin	17	OUT2	Motor output pin
8	IN3	Motor control input pin	18	IM	Current sense resistor
9	IN4	Motor control input pin	19	GND	Controller and driver ground
10	VB	Power supply pin for motor driver	20	OUT1	Motor output pin



## Absolute Maximum Ratings ( Unless otherwise noted, $T_A=25^\circ C$ )

Characteristic	Symbol	Rating	Unit
Supply Voltage	$V_{DD}$	5.5	V
	$V_B$	5.5	V
Input Voltage	$V_{IN}$	$V_{DD}+0.4$	V
$I_O$ Peak Current	$I_{OPeak}$	1.5	A
$I_{ODC}$ Current	$I_{ODC}$	550	mA
Power Dissipation	$P_D$	800	mW
Operating Temperature Range	$T_{OPR}$	-40 ~ 125	°C
Storage Temperature Range	$T_{STG}$	-65 ~ 150	°C

## Electrical Characteristic

(Unless otherwise noted,  $T_A=25^\circ C$  ,  $R_a + R_b = 10 k\Omega$  &  $V_{DD} = V_B = 3V$  )

Characteristic	Sym.	Condition	Limit			Unit
			Min.	Typ.	Max.	
Supply Voltage	$V_{DD}$		2.2	3	5.5	V
	$V_B$		-	3	5.5	V
Supply Current ( $I_{DD}$ )	$I_{STB}$	$V_{EN1 \sim EN2} = L$ ; $V_{IN1 \sim IN4} = L$	-	0.1	1	$\mu A$
	$I_{DD1}$	$V_{EN1 \sim EN2} = LH$	-	0.8	1.5	mA
	$I_{DD2}$	$V_{EN1 \sim EN2} = HL$	-	0.6	1.0	mA
	$I_{DD3}$	$V_{EN1 \sim EN2} = HH$	-	0.6	1.0	mA
Reference Voltage Circuit						
Reference Voltage	Vref	$V_{DD} = 3V$ ; $I_{ref} = -1mA$	1.19	1.23	1.27	V
EN1~2 / IN1~4 Input Terminal ( $T_J = 25^\circ C$ )						
Input Voltage "H"	$V_{IH}$	-	$0.8 * V_{DD}$	-	$V_{DD} + 0.4$	V
Input Voltage "L"	$V_{IL}$	-	-0.4	-	$0.2 * V_{DD}$	V
Input Current "H"	$I_{IH}$	$V_{IN} = V_{DD}$	-	-	$\pm 5$	$\mu A$
Input Current "L"	$I_{IL}$	$V_{IN} = 0 V$	-	-	$\pm 5$	$\mu A$
AF Output Terminal (OUT2-3 , OUT5-6)						
Saturation Voltage (upper + lower)	$V_{SAT1}$	$I_{OUT} = 200 mA$	-	0.25	0.4	V
AE Output Terminal (OUT4-5)						
Saturation Voltage (upper + lower)	$V_{SAT2}$	$I_{OUT} = 200 mA$	-	0.25	0.4	V



SH Output Terminal (OUT1-2)								
Output Current1		I <sub>O1</sub>	O2-> O1, R <sub>IM</sub> = 1Ω V <sub>IAD</sub> =0.3V		255	270	285	mA
Output Current1		I <sub>O2</sub>	O1-> O2, R <sub>PIM</sub> = 0.9Ω V <sub>IAD</sub> =0.3V		220	248	275	mA
Saturation Voltage (upper + lower)		V <sub>SAT3</sub>	I <sub>OUT</sub> = 200 mA		-	0.25	0.4	V
Thermal Protection Circuit								
Protection Temperature		T <sub>TSD</sub>	V <sub>EN1</sub> or V <sub>EN2</sub> =H		-	160	-	°C


## Truth Table

INPUT						OUTPUT						MODE
EN1	EN2	IN1	IN2	IN3	IN4	O1	O2	O3	O4	O5	O6	
L	L	—	—	—	—	—	—	—	—	—	—	STB
L	H	L	L			—	—	—				SH
		L	H			L	H	—				
		H	L			H	L	—				
		H	H			—	—	—				
				L	L			—	—	—	—	
				L	H			—	L	H	—	
				H	L			—	H	L	—	
				H	H			—	—	—	—	
H	L	L	L			—	—	—				AE (VCM)
		L	H			—	—	L				
		H	L			—	—	H				
		H	H			—	—	—				
				L	L			—	—	—	—	
				L	H			—	L	H	—	
				H	L			—	H	L	—	
				H	H			—	—	—	—	
H	H	L	L			—	—	—				AF (STM)
		L	H			—	L	H				
		H	L			—	H	L				
		H	H			—	—	—				
				L	L			—	—	—	—	
				L	H			—	L	H	—	
				H	L			—	H	L	—	
				H	H			—	—	—	—	


Note: “\*”: Don't care; “—”: High Impedance

## Application Circuit

- AF: Saturation drive for 2 phase, 1-2 phase stepping motor
- M-shutter: Constant current drive for shutter voice coil motor
- Aperture: Saturation drive for aperture voice coil motor



## Function Block (TSSOP-20 Pin Assignment)



## Application Notes

- The 11-MD142 integrates saturation voltage and constant current of motor driver. The range of supply voltage of 11-MD142, VDD and VB, is from 2.2V to 5.5V. The 11-MD142 input range is defined that logic “H” is from 0.8\*VDD to VDD+0.4V and logic “L” is from -0.4V to 0.2\*VDD. EN1 and EN2 are mode selection pins; IN1, IN2, IN3 and IN4 are motor rotation selection pins.
- Normally VB should provide enough current for output loading, thus large value of C is suggested for the terminal VB. Besides, 0.01uF~0.1uF of capacitors, C<sub>n</sub>, are also suggested between each output channel and output channel to ground.
- Constant current operation of 11-MD142 provides the current, which can be evaluated by the following formula (See the depiction of application circuit 1.):

$$I_{PIM} = \frac{V_{IAD}}{(R_{PIM} + 0.3)} \quad (unit : A)$$


$$I_{IM} = \frac{V_{IAD}}{(R_{IM} + 0.11)} \quad (unit : A)$$

- Before switching the mode of actuator, make sure to pull low the motor rotation selection pins (IN1~IN4). Then, switch to next mode to drive the motor.
- Considering of stability of function of constant current, compensation capacitor of C<sub>c</sub> (0.1~1uF) is suggested to connect between pin OUT1 and IM.





## Package Specifications (QFN-32)

TOP VIEW





BOTTOM VIEW



Note: "DDDDDDDD" are the date code or lot number and may be changed.

SYMBOL	Dimensions in Millimeter		
	MIN	NOM	MAX
A	0.70	0.75	0.80
A1	0	0.02	0.05
A3	0.20	REF	
b	0.18	0.25	0.30
D	5.00	BSC	
D2	2.60	2.70	2.80
E	5.00	BSC	
E2	2.60	2.70	2.80
L	0.30	0.40	0.50
e	0.50	BSC	

## Package Specifications(TSSOP-20)



Note: "DDDDDDDD" are the date code or lot number and may be changed.

SYMBOL	Dimensions in Millimeter		
	MIN	NOM	MAX
A	—	—	1.20
A1	0.05	—	0.15
A2	0.80	1	1.05
b	0.19	—	0.30
C	0.09	—	0.20
D	6.40	6.50	6.60
E	6.20	6.40	6.40
E1	4.30	4.40	4.50
e	—	0.65	—
L	0.45	0.60	0.75
y	—	—	0.10
$\theta$	0°	—	8°



The products listed herein are designed for ordinary electronic applications, such as electrical appliances, audio-visual equipment, communications devices and so on. Hence, it is advisable that the devices should not be used in medical instruments, surgical implants, aerospace machinery, nuclear power control systems, disaster/crime-prevention equipment and the like. Misusing those products may directly or indirectly endanger human life, or cause injury and property loss.

Silicon Touch Technology, Inc. will not take any responsibilities regarding the misusage of the products mentioned above. Anyone who purchases any products described herein with the above-mentioned intention or with such misused applications should accept full responsibility and indemnify. Silicon Touch Technology, Inc. and its distributors and all their officers and employees shall defend jointly and severally against any and all claims and litigation and all damages, cost and expenses associated with such intention and manipulation.