



44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089

## NTE1836 Integrated Circuit Electronic Channel Select System Control

### **Description:**

The NTE1836 contains CPU/PLL-excluded peripheral circuits such as band switch, +5V power supply (with  $\overline{RST}$ ), sync detector, low-pass filter for color TV/VCR frequency synthesizer channel select system use.

### **Functions:**

- Band Switch (2-Input, 4-Output)
- Video Signal, Flyback Pulse, AFT Output—Used Detection of Tuning Mode and Horizontal Sync Mode
- +5V Power Supply, with  $\overline{RST}$  Output (for CPU)
- OP Amp for Low-Pass Filter (for Frequency Synthesizer)

### **Features:**

- The Band Switch Truth Table can be changed in a short period of time at the user's option.
- The Band Switch is of PNP output type which need not be driven externally.
- The OP Amp for Low-Pass Filter is excellant in pulse response because of it's High-Impedance Input Pin.

### **Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$ unless otherwise specified)

Allowable Power Dissipation ( $T_A \leq +65^\circ\text{C}$ ), $P_{D\max}$ . . . . .	770mW
Operating Temperature Range, $T_{opr}$ . . . . .	-20° to +65°C
Storage Temperature Range, $T_{stg}$ . . . . .	-55° to +125°C

### **Band Switch Section**

$V_{CC1}$ Maximum Supply Voltage, $V_{13\max}$ . . . . .	15V
Maximum Load Current, $I_{14}, I_{15}, I_{16}, I_{17\max}$ . . . . .	-40mA
Maximum Applied Voltage (Output OFF), $V_{14}, V_{15}, V_{16}, V_{17\max}$ . . . . .	-15V
Maximum Applied Voltage (Input, $V_{cc} = 14V$ ), $V_6\max, V_7\max$ . . . . .	12V

### **+5V Power Supply Section**

$V_{CC2}$ Maximum Supply Voltage, $V_{10\max}$ . . . . .	15V
+5V Output Current, $I_8\max$ . . . . .	-30mA

**Maximum Ratings Cont'd):** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

#### Tuning Detector Section

Maximum Input Voltage, $V_2\text{max}$	.....	3.5V
Maximum Input Voltage (Negative Polarity), $-V_2\text{max}$	.....	-1.4V
Maximum Comparator Difference Voltage, $V_{19} - V_{20}$	.....	6V

#### Low-Pass Filter Section

Maximum Applied Voltage, $V_{12}\text{max}$	.....	35V
Maximum Input Voltage, $V_{11}\text{max}$	.....	5.9V

**Recommended Operating Conditions:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Min	Typ	Max	Unit
Supply Voltage Range ( $V_{CC1}$ )	$V_{10}$	9.0	12.0	14.0	V
	$V_{13}$	9.0	12.0	14.0	
Output Current (Tuning Detection Section)	$I_4, I_5$	—	—	3	mA
Load Current (LPF Section)	$I_{12}$	—	3	5	mA
Comparator Voltage Setting Range (Tuning Detector Section)	$V_{19}$	2.7	—	7.0	V

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$ ,  $V_{CC1} = 12\text{V}$ ,  $V_{CC2} = 12\text{V}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
<b>Band Switch Section</b>						
Quiescent Current Dissipation	$I_{CC1}$		—	16.0	—	mA
Output Saturation Voltage	$F_1$ to 4 sat	$I_O = -40\text{mA}$	0	—	0.7	V
Input "H" Level Voltage	$V_{6TH}, V_{7TH}$		2.2	—	—	V
Input "L" Level Voltage	$V_{6TL}, V_{7TL}$		0	—	0.8	V
Output Leakage Current	$I_{FL}$	$-15\text{V}$	—	—	-50	$\mu\text{A}$
<b>+5V Power Supply Section</b>						
Quiescent Current Dissipation	$I_{CC2}$		—	3.6	—	mA
+5V Output Voltage	$V_8$	$I_8 = -30\text{mA}$	4.7	—	5.3	V
RST Output Voltage	$V_{9sat}$	$I_9 = -100\mu\text{A}$	4.7	—	5.3	V
<b>Tuning Detection Section</b>						
Input Threshold Voltage	$V_{2TH}$		0.6	0.72	1.5	V
Comparator Voltage	$V_{C19}$		3.7	4.0	4.3	V
Window Comparator "H" Voltage	$V_{CH}$		7.7	8.0	8.3	V
Window Comparator "L" Voltage	$V_{CL}$		3.7	4.0	4.3	V
Output Saturation Voltage	$V_{4sat}$	$I_{sink} = 2\text{mA}$	0	0.33	0.7	V
	$V_{5sat}$	$I_{sink} = 2\text{mA}$	0	0.33	0.7	
Low-Pass Filter Output Current	$I_{OL}$		-1.85	-1.39	-1.12	mA
<b>LPF Section</b>						
Output Saturation Voltage	$V_{12sat}$		0	—	0.3	V
Input Threshold Voltage	$V_{11TH}$		2.0	—	2.4	V
Input Current	$I_{11}$		—	—	20	nA

### Band Switch Truth Table

Input		Output			
A (Pin7)	B (Pin6)	F <sub>1</sub> (Pin14)	F <sub>2</sub> (Pin15)	F <sub>3</sub> (Pin16)	F <sub>4</sub> (Pin17)
L	L	H	Z	Z	Z
H	L	Z	H	Z	Z
L	H	Z	Z	H	Z
H	H	Z	Z	Z	H

Z: High Impedance

### Operation of Tuning Detection Section

Tuning Mode	LPF Output	AFT	OUT1	OUT2
Unsynchronized	L	AFT-L	L	L
		AFT-C	L	L
		AFT-H	L	L
Synchronized	H	AFT-L	H	L
		AFT-C	H	H
		AFT-H	L	H

AFT-L:  $V_{AFT} < V_{CL}$

AFT-C:  $V_{CL} < V_{AFT} < V_{CH}$

AFT-H:  $V_{AFT} > V_{CH}$

### Pin Connection Diagram



