

# JPAD200 LOW LEAKAGE PICO-AMP DIODE



# Linear Systems replaces discontinued Siliconix JPAD200

# The JPAD200 is a low leakage Pico-Amp Diode packaged in TO-92

The JPAD200 extremely low-leakage diode provides a superior alternative to conventional diode technology when reverse current (leakage) must be minimized. The JPAD200 features a leakage current of -200 pA and is well suited for use in applications such as input protection for operational amplifiers.

#### JPAD200 Benefits:

- Negligible Circuit Leakage Contribution
- Circuit "Transparent" Except to Shunt High-Frequency Spikes
- Simplicity of Operation

### JPAD200 Applications:

- Op Amp Input Protection
- Multiplexer Overvoltage Protection

FEATURES					
DIRECT REPLACEMENT FOR SILICONIX JPAD200					
REVERSE BREAKDOWN VOLTAGE BV <sub>R</sub> ≥ -35V					
ULTRALOW LEAKAGE	≤ 200 pA				
REVERSE CAPACITANCE	C <sub>rss</sub> ≤ 2.0pF				
ABSOLUTE MAXIMUM RATINGS	×				
@ 25°C (unless otherwise noted)	>				
Maximum Temperatures					
Storage Temperature	ature -65°C to +150°C				
erating Junction Temperature -55°C to +135°C					
Maximum Power Dissipation	21				
Continuous Power Dissipation 350mW					
MAXIMUM CURRENT					
Forward Current (Note 1)	10mA				

JPAD200 ELECTRICAL CHARACTERISTICS @ 25°C (unless otherwise noted)

SYMBOL	CHARACTERISTICS	MIN.	TYP.	MAX.	UNITS	CONDITIONS
BV <sub>R</sub>	Reverse <mark>Br</mark> eakdown Voltage	<del>-3</del> 5-	1		V	- I <sub>R</sub> =-1μΑ
V <sub>F</sub>	Forward Voltage		0.8	1.5	V	I <sub>F</sub> = 5mA
$C_{rSS}$	Total Reverse Capacitance		1.5	2	pF	$V_R = -5V$ , $f = 1MHz$
I <sub>R</sub>	Maximum Reverse Leakage Current		-	-200	pA	V <sub>R</sub> = - 20V

#### Notes:

1. Absolute maximum ratings are limiting values above which JPAD200 serviceability may be impaired.

#### Available Packages:

JPAD200 in TO-92

JPAD200 available as bare die

Please contact Micross for full package and die dimensions




### Micross Components Europe

Tel: +44 1603 788967

Email: <a href="mailto:chipcomponents@micross.com">chipcomponents@micross.com</a>
Web: <a href="http://www.micross.com/distribution.com">http://www.micross.com/distribution.com</a>

## TO-92 (Bottom View)



Information furnished by Linear Integrated Systems and Micross Components is believed to be accurate and reliable. However, no responsibility is assumed for its use; nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Linear Integrated Systems.