

# **Temperature Compensated Crystal Oscillators**

## NTC-4000 SERIES TCXO LEADED PACKAGE

#### **Analog Compensated**



The common thread running through the NTC-4000 TCXO family is its use of our custom bipolar three segment compensation IC. In addition to the IC and the crystal, these oscillators have adjustable thick film resistors for compensation and varactors to provide the changing reactance for temperature compensation. The NTC-4000 Series is available in a hermetically sealed, leaded DIP.

The custom IC offers several additional benefits. There is a built in automatic gain control circuit to decrease starting time, improve output level consistency and minimize the effects of crystal starting resistance. A

low noise regulator is also integrated; thus any voltage variations in the regulator over temperature are compensated. The low noise bipolar circuits also provide superior sideband noise performance. A buffer amplifier is also included to minimize load pull.

NTC-4000 TCXOs feature:

☐ 0.820 x 0.520 x 0.245 inches hermetic, leaded DIP

☐ Current drain of 2.5 mA

☐ DC voltage frequency adjustment

☐ Sinewave output

## **Specifications**

Reference Oscillator Frequency Range: 12.8 to 20 MHz

Standard Frequencies: 12.8 MHz

14.4 MHz 16.8 MHz

Frequency Stability vs temperature: ±2 ppm

-30°C to +85°C

aging:  $< \pm 1$  ppm/year, max  $< \pm 7$ ppm/10 years

Operating Temperature Range -30°C to +85°C

Supply Voltage +5V±10%

Current Drain 2.5 mA into 1K//15pF

Output Waveform sinewave

Output Level Range 200 mVp-p to 1.2 Vp-p

Frequency Adjustment Range ±10 ppm to ±17 ppm


Phase Noise -145 dBc/Hz at 10 kHz offset

## **Temperature Compensated Crystal Oscillators**




## NTC-4000 SERIES TCXO LEADED PACKAGE


### **PACKAGE (DIMENSIONS IN INCHES)**




## FREQUENCY VS TEMPERATURE



#### **TEST CIRCUIT**





## • NEL TCXO PART NUMBER DEVELOPMENT •

