



# Sparkle Power Inc.

A Leading Power Supply Manufacturer

Web site: [www.sparklepower.com](http://www.sparklepower.com)

## FSP150-ABBN1

**(Efficiency Level V, RoHS Compliant)**

**150 Watts Power Adapter**



### Features

- High efficiency and reliability
- Low noise and ripple
- Output over voltage, short circuit, and over current protection
- Complies with FCC part 15, and CISPR 22 class B
- Approved by CUL/UL60950-1 2<sup>nd</sup>, TUV EN60950-1 2<sup>nd</sup>, CB 60950-1 2<sup>nd</sup>, FCC, EMC

### Specification

- **Temperature Range:** Operating: 0°C ~ +40°C
- **Humidity:** 80% on operating, 90% on storage
- **Average Efficiency:** Efficiency Level V & ErP Teir 2
- **No Load Power Consumption:** Less than 0.5W
- **Dimensions (LxWxH):** 171x72x42mm  
/6.73x2.83x1.65inch

### Output Characteristics

SPI Model	Output Voltage	Output Current	Connector Type	Connector IDxODxL	Dc cable Length (mm)
AD150-ABBN1-ATC25	19V	7.89A	Barrel 180°	2.5x5.5.13	1500

**Sparkle Power Inc.**  
**Main Office**  
 1000 Rock Avenue  
 San Jose, CA 95131  
 TEL: 408-519-8888  
 FAX: 408-519-9999  
 E-MAIL: [info@sparklepower.com](mailto:info@sparklepower.com)

**Sparkle Power Inc.**  
**Los Angeles Office**  
 17071 Green Drive  
 City of Industry, CA 91745  
 TEL: 626-839-7180  
 FAX: 626-839-3395