

LOW POWER 32K X 8 STATIC CMOS RAM

FEATURES

- V_{cc} Current (Commercial/Industrial)
 - Operating: 70mA/85mA
 - CMOS Standby: 100µA/100µA
- Access Times
 - -55/70/85
- Wide Range Power Supply: 2.7V to 3.6V
- Easy Memory Expansion Using CE and OE Inputs
- Common Data I/O

- **■** Three-State Outputs
- **■** Fully TTL Compatible Inputs and Outputs
- Advanced CMOS Technology
- Automatic Power Down
- Packages
 - 28-Pin 600 mil DIP
 - 28-Pin 330 mil SOP
 - 28-Pin TSOP



DESCRIPTION

The P3C1256L is a 262,144-bit low power CMOS static RAM organized as 32Kx8. The CMOS memory requires no clocks or refreshing, and has equal access and cycle times. Inputs are fully TTL-compatible. The RAM operates with a wide range power supply (2.7V to 3.6V).


Access times of 55 ns and 70 ns are available. CMOS is utilized to reduce power consumption to a low level.

The P3C1256L device provides asynchronous operation


with matching access and cycle times. Memory locations are specified on address pins \underline{A}_0 to A_{14} . Reading is accomplished by device selection (\overline{CE} and output enabling (\overline{OE}) while write enable (\overline{WE}) remains HIGH. By presenting the address under these conditions, the data in the addressed memory location is presented on the data input/output pins. The input/output pins stay in the HIGH Z state when either \overline{CE} or \overline{OE} is HIGH or \overline{WE} is LOW.



FUNCTIONAL BLOCK DIAGRAM



PIN CONFIGURATIONS





RECOMMENDED OPERATING TEMPERATURE AND SUPPLY VOLTAGE

Temperature Range (Ambient)	Supply Voltage
Commercial (0°C to 70°C)	$2.7V \le V_{CC} \le 3.6V$
Industrial (-40°C to 85°C)	2.7V ≤ V _{CC} ≤ 3.6V
Military (-55°C to 125°C)	2.7V ≤ V _{CC} ≤ 3.6V

MAXIMUM RATINGS(1)

Sym	Parameter	Min	Max	Unit
V _{cc}	Supply Voltage with Respect to GND	-0.5	7.0	V
V _{TERM}	Terminal Voltage with Respect to GND (up to 7.0V)	-0.5	V _{cc} + 0.5	V
T _A	Operating Ambient Temperature	-55	125	°C
S _{TG}	Storage Temperature	-65	150	°C
I _{OUT}	Output Current into Low Outputs		25	mA
I _{LAT}	Latch-up Current	> 200		mA

DC ELECTRICAL CHARACTERISTICS

(Over Recommended Operating Temperature & Supply Voltage)(2)

Sym	Parameter	Test Conditions		Min	Max	Unit
V _{OH}	Output High Voltage (I/O ₀ - I/O ₇)	$I_{OH} = -1 \text{mA}, V_{CC} = 3.0 \text{V}$		2.4		V
V _{OL}	Output Low Voltage (I/O ₀ - I/O ₇)	I _{OL} = 2.1mA			0.4	V
V _{IH}	Input High Voltage			2.2	V _{CC} + 0.3	V
V _{IL}	Input Low Voltage			-0.5 ⁽³⁾	0.8	V
			Com	-2	+2	
I	Input Leakage Current	GND ≤ V _{IN} ≤ V _{CC}	Ind	-5	+5	μA
			Mil			
		OND AV	Com	-2	+2	
I _{LO}	Output Leakage Current	$\frac{\text{GND} \le \text{V}_{\text{OUT}} \le \text{V}_{\text{CC}}}{\overline{\text{CE}} = \text{V}_{\text{IH}}}$	Ind	-5	+5	μΑ
		OL - V _{IH}	Mil			
I _{SB}	V _{CC} Current TTL Standby Current (TTL Input Levels)	$V_{CC} = 3.6V$, $I_{OUT} = 0$ mA $\overline{CE} = V_{IH}$			3	mA
I _{SB1}	V _{CC} Current CMOS Standby Current (CMOS Input Levels)	$V_{CC} = 3.6V$, $I_{OUT} = 0$ mA $\overline{CE} \ge V_{CC} - 0.2V$			100	μА



CAPACITANCES⁽⁴⁾

 $(V_{CC} = 3.3V, T_A = 25^{\circ}C, f = 1.0MHz)$

Symbol	Parameter	Test Conditions	Max	Unit
C _{IN}	Input Capacitance	V _{IN} =0V	7	pF
C _{out}	Output Capacitance	V _{OUT} =0V	9	pF

POWER DISSIPATION CHARACTERISTICS VS. SPEED

Cress	Davanata:	Town and the Bonne	*			**			I I m i 4
Sym Parameter		Temperature Range	-55	-70	-85	-55	-70	-85	Unit
		Commercial	70	70	70	15	15	15	mA
I _{cc}	I _{cc} Dynamic Operating Current*	Industrial	85	85	85	25	25	25	mA
		Military	100	100	100	35	35	35	mA

^{*} Tested with outputs open and all address and data inputs changing at the maximum write-cycle rate. The device is continuously enabled for writing, i.e. $\overline{\text{CE}}$ and $\overline{\text{WE}} \leq \text{V}_{\text{IL}}$ (max), $\overline{\text{OE}}$ is high. Switching inputs are 0V and 3V.

AC ELECTRICAL CHARACTERISTICS—READ CYCLE


(Over Recommended Operating Temperature & Supply Voltage)

C:	Davision		55	-7	70	-8	35	l l m i f
Sym	ym Parameter		Max	Min	Max	Min	Max	Unit
t _{RC}	Read Cycle Time	55		70		85		ns
t _{AA}	Address Access Time		55		70		85	ns
t _{AC}	Chip Enable Access Time		55		70		85	ns
t _{oh}	Output Hold from Address Change	5		5		5		ns
t _{LZ}	Chip Enable to Output in Low Z	5		5		5		ns
t _{HZ}	Chip Disable to Output in High Z		20		25		30	ns
t _{oe}	Output Enable Low to Data Valid		30		35		40	ns
t _{OLZ}	Output Enable Low to Low Z	5		5		5		ns
t _{OHZ}	Output Enable High to High Z		20		25		30	ns
t _{PU}	Chip Enable to Power Up Time	0		0		0		ns
t _{PD}	Chip Disable to Power Down Time		55		70		85	ns


^{**} As above but @ f=1 MHz and $V_{\rm IL}/V_{\rm IH}$ = 0V/ $V_{\rm CC}$.




TIMING WAVEFORM OF READ CYCLE NO. 1 (OE CONTROLLED)(5)



TIMING WAVEFORM OF READ CYCLE NO. 2 (ADDRESS CONTROLLED)(5,6)



TIMING WAVEFORM OF READ CYCLE NO. 3 (ADDRESS CONTROLLED)(5,7)



Notes:

- Stresses greater than those listed under MAXIMUM RATINGS may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to MAXIMUM rating conditions for extended periods may affect reliability.
- 2. Extended temperature operation guaranteed with 400 linear feet per minute of air flow.
- 3. Transient inputs with V_{iL} and I_{iL} not more negative than -3.0V and -100mA, respectively, are permissible for pulse widths up to 20 ns.
- 4. This parameter is sampled and not 100% tested.
- 5. WE is HIGH for READ cycle.
- 6. $\overline{\text{CE}}$ is LOW and $\overline{\text{OE}}$ is LOW for READ cycle.
- 7. ADDRESS must be valid prior to, or coincident with $\overline{\text{CE}}$ transition LOW.
- Transition is measured ± 200 mV from steady state voltage prior to change, with loading as specified in Figure 1. This parameter is sampled and not 100% tested.
- Read Cycle Time is measured from the last valid address to the first transitioning address.




AC CHARACTERISTICS—WRITE CYCLE

(Over Recommended Operating Temperature & Supply Voltage)

Cumbal	Boundary	-55		-7	70	-8	35	I I mit
Symbol	Parameter	Min	Max	Min	Max	Min	Max	Unit
t_{wc}	Write Cycle Time	55		70		85		ns
t _{cw}	Chip Enable Time to End of Write	50		60		75		ns
t _{AW}	Address Valid to End of Write	50		60		75		ns
t _{AS}	Address Setup Time	0		0		0		ns
t_{WP}	Write Pulse Width	40		50		60		ns
t _{AH}	Address Hold Time	0		0		0		ns
t _{DW}	Data Valid to End of Write	25		30		35		ns
$t_{_{\mathrm{DH}}}$	Data Hold Time	0		0		0		ns
t _{wz}	Write Enable to Output in High Z		25		30		35	ns
t _{ow}	Output Active from End of Write	5		5		5		ns

TIMING WAVEFORM OF WRITE CYCLE NO. 1 (WE CONTROLLED)(10,11)




- 10. $\overline{\text{CE}}$ and $\overline{\text{WE}}$ must be LOW for WRITE cycle.
- 11. \overline{OE} is LOW for this WRITE cycle to show t_{WZ} and t_{OW} .

 12. If \overline{CE} goes HIGH simultaneously with \overline{WE} HIGH, the output remains in a high impedance state
- 13. Write Cycle Time is measured from the last valid address to the first transitioning address.



TIMING WAVEFORM OF WRITE CYCLE NO. 2 (CE CONTROLLED)(10)



AC TEST CONDITIONS

Input Pulse Levels	GND to 3.0V
Input Rise and Fall Times	3ns
Input Timing Reference Level	1.5V
Output Timing Reference Level	1.5V
Output Load	See Figures 1 and 2

TRUTH TABLE

Mode	CE	ŌĒ	WE	I/O	Power
Standby	Н	Х	Х	High Z	Standby
Standby	Х	Х	Х	High Z	Standby
D _{OUT} Disabled	L	Н	Н	High Z	Active
Read	L	L	Н	D _{OUT}	Active
Write	L	Х	L	High Z	Active




Figure 1. Output Load

Figure 2. Thevenin Equivalent

Note:

Because of the high speed of the P3C1256L, care must be taken when testing this device; an inadequate setup can cause a normal functioning part to be rejected as faulty. Long high-inductance leads that cause supply bounce must be avoided by bringing the $V_{\rm CC}$ and ground planes directly up to the contactor fingers. A 0.01 μF high frequency capacitor

is also required between V_{cc} and ground. To avoid signal reflections, proper termination must be used; for example, a 50Ω test environment should be terminated into a 50Ω load with 1.77V (Thevenin Voltage) at the comparator input, and a 589Ω resistor must be used in series with D_{OUT} to match 639Ω (Thevenin Resistance).

 $R_{TH} = 638.7\Omega$ $V_{TH} = 1.77 V$ $30pF^* (5pF^* \text{ for } t_{HZ}, t_{LZ}, t_{OHZ}, t_{OLZ}, t_{WZ} \text{ and } t_{OW})$

^{*} including scope and test fixture.




DATA RETENTION CHARACTERISTICS

Sym	Parameter	Test Conditions	Min	Ty V _c	p.* c =		ax c =	Unit
				2.0V	3.0V	2.0V	3.0V	
V _{DR}	V _{cc} for Data Retention		2.0					٧
I _{CCDR}	Data Retention Current	CE ≥ V _{CC} - 0.2V,		10	15	80	120	μA
t _{CDR}	Chip Deselect to Data Retention Time	$V_{IN} \ge V_{CC} - 0.2V$	0					ns
t _R †	Operation Recovery Time	or V _{IN} ≤ 0.2V	t _{RC} §					ns

^{*} TA = +25°C

DATA RETENTION WAVEFORM




 t_{RC} = Read Cycle Time

^{† =} This parameter is guaranteed but not tested.




ORDERING INFORMATION







~						
Pkg #	P6					
# Pins	28 (600 mil)					
Symbol	Min	Max				
Α	0.090	0.200				
A1	0.000	0.070				
b	0.014	0.020				
b2	0.015	0.065				
С	0.008	0.012				
D	1.380	1.430				
Е	0.485	0.550				
E1	0.600	0.625				
е	0.100 BSC					
eВ	0.600 TYP					
L	0.100 0.18					
	0°	15°				

PLASTIC DUAL IN-LINE PACKAGE










Pkg #	S11-3					
# Pins	28 (330 Mil)					
Symbol	Min	Max				
Α	0.094	0.120				
A1	0.002	0.014				
В	0.014	0.020				
С	0.008	0.012				
D	0.702	0.728				
е	0.050	BSC				
Е	0.291	0.340				
Н	0.463	0.477				
h	0.010	0.029				
L	0.020	0.050				
	0°	8°				

SOIC/SOP SMALL OUTLINE IC PACKAGE











•		
Pkg #	T1	
# Pins	28	
Symbol	Min	Max
Α	0.039	0.047
A_2	0.036	0.040
b	0.007	0.011
D	0.461	0.469
Е	0.311	0.319
е	0.022 BSC	
H	0.520	0.535

TSOP THIN SMALL OUTLINE PACKAGE



NOTE:

Orientation ID is either next to Pin 1 (midway along row of pins) or in corner on side of package containing Pin 1.





REVISIONS

DOCUMENT NUMBER	ER SRAM143	
DOCUMENT TITLE	P3C1256L LOW POWER 32K x 8 STATIC CMOS RAM	

REV	ISSUE DATE	ORIGINATOR	DESCRIPTION OF CHANGE
OR	Jul-2011	JDB	New Data Sheet
Α	Oct-2011	JDB	Added wide range power supply